
Release Notes - Zebra TC8000 Android L NGMS – LifeGuard Update 08 Release

Contents

[Description](#)

[Device Compatibility](#)

[Component Contents](#)

[Installation Requirements](#)

[Installation Instructions](#)

[Downloadable Software included in this Release](#)

Description

This release contains the following software package which is compatible with the TC8000 NGMS product.

LifeGuard patches are cumulative and include all previous fixes that are part of earlier patch releases

Note: Downgrade to Patch 6 or older patch version are not allowed on TC8000L devices which contains Hynix 16gb A15nm eMMC Memory.

1. CFE v8 Updates:

❖ CFE-TC8000-L-XX-021002-N-00-08.zip (NGMS)

❖ **Android Security Patch Level:** March 05, 2018

Use the below link to see the Android Security bulletin for more information:

<https://source.android.com/security/bulletin/>

- Spectre & Meltdown correction for variant 1 and variant 2
- SPR33599 – Resolved an issue wherein few of the system applications are getting disabled after enabling whitelist.
- SPR33799 - Resolved an issue wherein scanner was unable to read '\n' and '\r'.
- SPR33930 - Resolved an issue wherein dhcp address was not acquired by the device, while hostname is greater than 32 characters.
- SPR33973- Resolved an issue wherein erroneously loading default profile by providing feature to ignore disabled profiles in DataWedge.
- SPR33671- Resolved an issue wherein user was unable to create WIFI profile with username as backslash followed by number.
- Updated below mentioned components:
 - File Browser: 1.19.12
 - Diagnostic Tool: 1.15.0.11
 - Scanner Framework: 19.9.35.0
 - Radio: 2.00.0.0.009

- Bluetooth: 01.12.00

2. CFE v7 Updates:

- ❖ CFE-TC8000-L-XX-021002-N-00-07.zip (NGMS)
 - SPR33674- Resolved a flash corruption issue with multiple symptoms like unable to turn on WIFI.
 - SPR33823 - Resolved an issue wherein black screen occurred in DataWedge application.
 - Updated below mentioned components:
 - Datawedge: 6.7.47
 - StageNow: 2.10.1.1389
 - EMDK: 6.8.21.1121
 - MX: 7.2.1.0

3. CFE v6 Updates:

- ❖ CFE-TC8000-L-XX-021002-N-00-06.zip (NGMS)
 - ❖ **Android Security Patch Level:** January 05, 2018
Use the below link to see the Android Security bulletin for more information:
<https://source.android.com/security/bulletin/>

4. CFE v5 Updates:

- ❖ CFE-TC8000-L-XX-021002-N-00-05.zip (NGMS)
 - ❖ **Android Security Patch Level:** December 05, 2017
Use the below link to see the Android Security bulletin for more information:
<https://source.android.com/security/bulletin/>
 - SPR32988 - Resolved an issue wherein the BUTTON_R2 has been consumed by both barcode scanner and Google chrome client.
 - SPR33233 - Resolved an issue wherein the DataWedge 6.2.24 could not replace separator or non-printable ascii character with \$.
 - SPR32825 - Resolved an issue wherein BT headset volume up/down was not working during Bluetooth call scenario.
 - SPR32463 - Resolved an issue wherein the StageNow File Manager downloads frequently fails due to Sockettimeout exception.
 - Updated below mentioned components:
 - Datawedge: 6.6.49
 - StageNow: 2.9.1.1344
 - EMDK: 6.7.10.1010
 - MX: 7.1.1.0

5. CFE v4 Updates:

- ❖ CFE-TC8000-L-XX-021002-N-00-04.zip (NGMS)
 - ❖ **Android Security Patch Level:** September 05, 2017
Use the below link to see the Android Security bulletin for more information:
<https://source.android.com/security/bulletin/>
 - Corrections for KRACK vulnerabilities applied.
 - SPR30400/31340 – Added support to enable/disable Network Monitoring Notification.

6. CFE v3 Updates:

- ❖ CFE-TC8000-L-XX-021002-N-00-03.zip (NGMS)

❖ **Android Security Patch Level:** September 05, 2017

Use the below link to see the Android Security bulletin for more information:

<https://source.android.com/security/bulletin/>

- Updated below mentioned components:
 - MXMF - Version 7.0.2.1
 - DataWedge - Version 6.5.61
 - EMDK - Version 6.6.14.914
 - Staging Client - Version 2.8.1.1221
- Resolved an issue in MX to prevent leakage of configuration parameters.
- Included fix for BlueBorne vulnerability.
- SPR31745 - Resolved an issue wherein AOSP doesn't returns a network interface address when myIpAddress/myIpAddressEx is queried.
- SPR32373 - Resolved an issue wherein the barcode data is not transmitted when "All Decoders" is unchecked and every single decoder is checked.
- SPR32582 - Added support for Netherlands - Belgium language.
- SPR32008_SPR31820 - Resolved an issue wherein scanning PDF417 barcodes which contain embedded 0x0D characters resulted in continuous line of data instead of displaying in different lines.
- SPR32132/SPR32896 - Resolved an issue wherein wifi was getting disabled intermittently when the battery hot swaps were done frequently.
- SPR32676 - Resolved an issue wherein DataWedge App crashes when Velocity App tries to send an Intent to enable the scanner plugin.
- SPR32775 - Resolved an issue wherein the notification class created with FLAG_INSISTENT was not getting cleared upon pulling down the notification drawer.

7. CFE v2 Updates:

❖ CFE-TC8000-L-XX-021002-N-00-02.zip (NGMS)

❖ **Android Security Patch Level:** August 05, 2017

Use the below link to see the Android Security bulletin for more information:

<https://source.android.com/security/bulletin/>

- SPR29912 - Resolved an issue wherein certificates installation failed through stagenow.
- SPR30401 - Added support to get the CFE version via MDM clients.
- SPR31954 - Resolved an issue wherein dhcpd was not able to start due to lengthy host name.
- SPR32135 - Resolved an issue wherein Settings screen does not revert to its normal state even though the locale language is changed from Arabic to English via EMDK.
- SPR32240 - Resolved an issue wherein the scanner service was not responding while switching between applications.
- SPR32193_SPR32230 - Resolved an issue wherein devices experiencing authentication failures, and were not able to recover.
- SPR32539 - Resolved an issue wherein build certificates were lost randomly even though certificates were not expired.
- SPR32355 - Resolved an issue wherein dhcp was not able to start due to lengthy host name.
- SPR32413 - Resolved an issue wherein after selecting the static option in the ethernet settings, changes are not reflecting in interface and the interface was always dhcp.
- SPR32326 - Resolved an issue wherein Settings application crashed while trying to set enterprise keyboard as the default keyboard and disable AOSP keyboard through the stageNow profile.

8. CFE v1 Updates:

❖ CFE-TC8000-L-XX-021002-N-00-01.zip (NGMS)

❖ **Android Security Patch Level:** July 05, 2017

Use the below link to see the Android Security bulletin for more information:

<https://source.android.com/security/bulletin/>

- Added Zebra patch version value in Settings to identify the CFE Patch version.

Device Compatibility

This software release has been approved for Android TC8000 L models mentioned below.

| Device | Operating System |
|-------------------|------------------|
| TC80N0-A000K110NA | Android 5.1.1 |
| TC80N0-1000K210NA | Android 5.1.1 |
| TC80N0-2000K210NA | Android 5.1.1 |
| TC80N0-3000K210NA | Android 5.1.1 |
| TC80N0-A001K31CNA | Android 5.1.1 |
| TC80N0-1001K31CNA | Android 5.1.1 |
| TC80N0-2001K31CNA | Android 5.1.1 |
| TC80N0-3001K31CNA | Android 5.1.1 |
| TC80NH-A101K320NA | Android 5.1.1 |
| TC80NH-1101K420NA | Android 5.1.1 |
| TC80NH-2101K420NA | Android 5.1.1 |
| TC80NH-3101K420NA | Android 5.1.1 |
| TC80N0-1101K42ENA | Android 5.1.1 |
| TC80N0-A000K110IN | Android 5.1.1 |
| TC80N0-1000K210IN | Android 5.1.1 |
| TC80N0-2000K210IN | Android 5.1.1 |
| TC80N0-3000K210IN | Android 5.1.1 |
| TC80N0-A001K31CIN | Android 5.1.1 |
| TC80N0-1001K31CIN | Android 5.1.1 |
| TC80N0-2001K31CIN | Android 5.1.1 |
| TC80N0-3001K31CIN | Android 5.1.1 |
| TC80NH-A101K320IN | Android 5.1.1 |
| TC80NH-1101K420IN | Android 5.1.1 |
| TC80NH-2101K420IN | Android 5.1.1 |
| TC80NH-3101K420IN | Android 5.1.1 |
| TC80N0-1101K42EIN | Android 5.1.1 |
| TC80NH-2101K42ENA | Android 5.1.1 |
| TC80NH-2101K42EIN | Android 5.1.1 |
| TC80NH-1102K420NA | Android 5.1.1 |
| TC80NH-3102K420NA | Android 5.1.1 |
| TC80NH-1102K420IN | Android 5.1.1 |
| TC80NH-3102K420IN | Android 5.1.1 |
| TC80NH-1101K42ENA | Android 5.1.1 |
| TC80NH-1101K42EIN | Android 5.1.1 |

Component Contents

| Component / Description | Version |
|---------------------------|------------------------|
| Product Base Build Number | 02-10-02-L-00-A |
| Zebra Patch Version | 8 |
| Android Version | 5.1.1 |
| Wi-Fi | FUSION_QA_2.00.0.0.016 |

| | |
|---------------|-------|
| SimulScanDemo | 3.0.2 |
| SimulScanRes | 2.0.2 |

Installation Requirements

- The Software update requires SKU hardware device.
- Enterprise Reset and Factory Reset package files are available on the TC8000 Software Download section on Zebra.com

Installation Instructions

BEFORE UPDATING THE OS IMAGE, EXTERNAL POWER MUST BE APPLIED TO THE TERMINAL VIA USB CHARGING CABLE OR CRADLE.

PLEASE ENSURE BATTERY LEVEL IS > 30%

CFE software update procedure for TC8000 NGMS:

1. Connect the USB cable from your PC to the device and enable USB mass storage mode on the device.
2. On your PC you should see an internal and external USB mass storage drive (SD card) appears in the File Explore and copy "**CFE-TC8000-L-XX-021002-N-00-08.zip**" file to any storage.
3. Press and hold on the device Power button, click on power off and wait until the screen is turned OFF.
4. Press and hold power, Vol+ button and Scanner button.
5. Keep holding all three buttons until the device vibrates.
6. Device should enter recovery mode.
7. if applying update via Sideload Method
 - a. Use the Volume + and – to highlight, “Apply update from ADB” and press the Scanner Key to select it
 - b. With your Command Prompt open in the Host machine, type “adb sideload” command and add a space and then drag and drop the CFE on to it and click enter.
 - c. Your PC screen will show files being installed and a little blue horizontal progress bar on your device will show status... and after about 6~ minutes it should be done and you should be back at the Android Recovery screen.
 - d. “*Reboot system now*” is highlighted. Press the Scanner Key to Reboot.
8. If applying update via SD card.
 - a. Click on Vol+ or Vol- to navigate and select SD card or internal storage. Press Scanner button to select it.
 - b. Click on Vol+ or Vol- to navigate to the recovery update zip file.
 - c. Click on Scanner button to select and start the recovery update process.
 - d. Device will automatically reboot and will be ready to use.

9. To Check the Android Patch Level after installing the CFE package in the device,
 - a. Settings->About Device->SW Components: Device Patch Version: 8
 - b. ADB Shell method: Execute following command from PC's command prompt:
\$ adb shell getprop ro.device.patch.version
\$ 8
10. Now you are all set to use your **TC8000**.

Downloadable Software Included in this Release

| Filename | Description |
|---|---|
| CFE-TC8000-L-XX-021002-N-00-08.zip | OTA incremental CFE v8 update software for NGMS build |

Last Revised: <04-25-2018>