

# Release Notes – Zebra Android 14

## 14-20-14.00-UG-U160-STD-ATH-04 Release (GMS)

### Highlights

This Android 14 GMS release 14-20-14.00-UG-U160-STD-ATH-04 covers TC22, TC27, TC53, TC58, TC73, TC78, HC20, HC50, ET60 and ET65 product. Please see device compatibility under Addendum Section for more details.

**This release requires a mandatory step OS Update method to upgrade to A14 BSP software from A11.** Please refer for more details under “OS Update Installation Requirements and Instructions” section.

### Software Packages

Package Name	Description
AT_FULL_UPDATE_14-20-14.00-UG-U160-STD-ATH-04.zip	Full package update
<p><b>For TC22, HC20 and HC50:</b></p> <p>AT_DELTA_UPDATE_14-20-14.00-UG-U116-STD_TO_14-20-14.00-UG-U160-STD.zip</p> <p><b>Other Devices:</b></p> <p>AT_DELTA_UPDATE_14-20-14.00-UG-U110-STD_TO_14-20-14.00-UG-U160-STD.zip</p>	<p><b>For TC22, HC20 and HC50:</b></p> <p>Delta package update from 14-20-14.00-UG-U116-STD TO 14-20-14.00-UG-U160-STD release</p> <p><b>Other Devices:</b></p> <p>Delta package update from 14-20-14.00-UG-U110-STD TO 14-20-14.00-UG-U160-STD release</p>

### Security Updates

This build is compliant up to [Android Security Bulletin](#) of February 01, 2025.

### LifeGuard Update 14-20-14.00-UG-U160

Adds Security updates to be compliant with [Android Security Bulletin](#) of February 01, 2025.

#### ○ New Features

#### ○ Resolved Issues

- SPR-54688 – Fixed an issue where sometimes orientation of locked screen not persisting.

- **Usage Notes**

- Due to new mandatory privacy requirements from Google, the Setup Wizard Bypass feature has been discontinued on devices running Android 13 and later. Consequently, it is now restricted to skip the Setup Wizard screen, and the StageNow barcode will not function during the Setup Wizard, displaying a toast message stating “Not supported.”
- If the Setup Wizard has already been completed and its data was configured to persist on the device in the past, there is no need to repeat this process following an Enterprise Reset.
- For more details, please refer to the Zebra FAQ documentation:  
<https://techdocs.zebra.com/zebradna/latest/faq/#setupwizardsuw>

## **LifeGuard Update 14-20-14.00-UG-U116**

Adds Security updates to be compliant with [Android Security Bulletin](#) of January 01, 2025.

- **New Features**

- **Resolved Issues**

- **Usage Notes**

- None

## **LifeGuard Update 14-20-14.00-UG-U110**

Adds Security updates to be compliant with [Android Security Bulletin](#) of January 01, 2025.

- **New Features**

- **Resolved Issues**

- **Usage Notes**

- None

## **LifeGuard Update 14-20-14.00-UG-U87**

- **New Features**

- **Camera:**

- Added support for camera driver for new 16MP rear camera module on TC53,TC58,TC73,TC78,ET60 & ET65 products.

### ○ Resolved Issues

- SPR54815 - Resolved an issue where in DWDemo issue with sending barcode data containing embedded TAB characters.
- SPR-54744 – Resolved an issue where in sometimes FFDservice feature was not working.
- SPR-54771 / SPR-54518 - Resolved an issue where in sometimes when device battery is critically low device stuck in boot screen.

### ○ Usage Notes

- Devices with the new camera module cannot be downgraded – the minimum build requirement on Android 11 is 11-42-08.00-RG-U00-STD-ATH-04 or newer, Android 13 is 13-39-18.00-TG-U00-STD-ATH-04 or newer and on Android 14 14-20-14.00-UG-U87-STD-ATH-04 or newer.
- To identify the new camera type user can check 'ro.boot.device.cam\_vcm' using getprop from the adb. Only new camera devices will have the below property:  
ro.boot.device.cam\_vcm=86021

## LifeGuard Update 14-20-14.00-UG-U57

### ○ New Features

- Added a new feature for the device microphone, which controls audio input through connected audio device
- Added support for WLAN TLS1.3

### ○ Resolved Issues

- SPR-54154 – Resolved an issue where in resetting the pending event flag to avoid radio power cycling loop

### ○ Usage Notes

- None

## LifeGuard Update 14-20-14.00-UG-U45

### ○ New Features

- FOTA:
  - Incremental software release with optimization and improvements for A14 OS support.
- Zebra Camera App:
  - Added 720p picture resolution.

- Scanner Framework 43.13.1.0:
  - Integrated latest OboeFramework library 1.9.x
- Wireless Analyser:
  - Stability fixes under Ping, Coverage View, disconnect scenarios while running Roam/Voice.
  - Added a new feature in Scan List to display the Cisco AP Name.

#### ◦ Resolved Issues

- SPR54043 – Resolved an issue where in scanner changes, Active Index should not be reset if clear submit failed.
- SPR-53808 – Resolved an issue where in few devices were unable to scan enhanced dot data matrix labels consistently.
- SPR54264 – Resolved an issue where in snap on trigger not working when DS3678 is connected.
- SPR-54026 – Resolved an issue where in EMDK Barcode parameters for 2D inverse.
- SPR 53586 - Resolved an issue where in battery draining was observed on few devices with external keyboard.

#### ◦ Usage Notes

- None

## LifeGuard Update 14-20-14.00-UG-U11

#### ◦ New Features

- Added a Allows User to select a portion of available device storage to be used as system RAM. This feature can be turned ON/OFF from device admin only. Please refer to <https://techdocs.zebra.com/mx/powermgr/> for more details
- **Scanner Framework 43.0.7.0**
  - FS40 (SSI Mode) Scanner Support with DataWedge.
  - Enhanced Scanning performance with SE55/SE58 Scan Engines.
  - Added support for RegEx checking in Free-Form OCR and Picklist + OCR Workflows.

#### ◦ Resolved Issues

- SPR-54342 – Fixed an issue where NotificationMgr feature support has been added which was not working.
- SPR-54018 – Fixed an issue where Switch param API is not working as expected when hardware trigger is disabled.
- SPR-53612 / SPR-53548 - Resolved an issue wherein a random double decode occurred while using the physical scan buttons on TC22/TC27 and HC20/HC50 devices.

- SPR-53784 - Resolved an issue wherein chrome changes tabs while using L1 and R1
- keycode

- **Usage Notes**

- None

## **LifeGuard Update 14-20-14.00-UG-U00**

- **New Features**

- Added a new feature to read EMMC flash data via EMMC app and adb shell.
- Wireless Analyzer(WA\_A\_3\_2.1.0.006\_U):
  - A full-functional real-time WiFi Analysis and troubleshooting tool to help analyze and resolve WiFi issues from a mobile device standpoint.

- **Resolved Issues**

- SPR-53899: Resolved an issue where all application permissions were accessible to the user in System restricted with Reduced Accessibility.
- SPR 53388: Firmware Update for SE55 (PAAFNS00-001-R09) Scan Engine with Critical bug fixes, and performance enhancements. This update is highly recommended.

- **Usage Notes**

- None

## **LifeGuard Update 14-18-19.00-UG-U01**

- LifeGuard Update 14-18-19.00-UG-U01 contains security updates only.
- This LG patch is applicable for 14-18-19.00-UG-U00-STD -ATH-04 BSP version.

- **New Features**

- None

- **Resolved Issues**

- None

- **Usage Notes**

- None

## LifeGuard Update 14-18-19.00-UG-U00

### ○ New Features

- The Hotseat home screen "**Phone**" icon has been replaced by the "**Files**" icon (For Wi-Fi-only devices).
- Added support for **Camera Stats** 1.0.3.
- Added support for **Zebra Camera App Admin control**.
- Added support for **DHCP Option** 119. (DHCP option 119 would work only on managed devices over WLAN only and WLAN profile should be created by device owner)
- **MXMF:**
  - DevAdmin adds the ability to control Android Lock Screen visibility on the remote console if the Lock Screen appears on a device while being remotely controlled.
  - Display Manager adds the ability to select screen resolution on the secondary display when a device is connected to an external monitor through a Zebra Workstation Cradle.
  - UI Manager adds the ability to control whether to display the remote-control icon in the Status Bar when the device is being remotely controlled or viewed.
- **DataWedge :**
  - Support has been added to enable and disable decoders, such as US4State and other Postal decoders, in the Free-Form Image Capture Workflow and other workflows where applicable.
  - New Point & Shoot feature: Allows the simultaneous capture of both barcodes and OCR (defined as a single alphanumeric word or element) by simply pointing at the target with the crosshair in the viewfinder. This feature supports both Camera and Integrated Scan Engines and eliminates the need to end the current session or switch between barcode and OCR functionalities.
- **Scanning:**
  - Added support for improved Camera scanning.
  - Updated SE55 firmware with R07 version.
  - Enhancements on Picklist + OCR allow capture of barcode or OCR by centering the desired target with the aiming crosshair/dot (Supports Camera and Integrated Scan Engines).
  - Enhancements on OCR also includes:
    - Text Structure: ability to capture a Single Line of text and the initial release of a single word.
    - Report Barcode Data Rules: ability to set rules for which barcodes to capture and report.
    - Picklist Mode: ability to allow for Barcode or OCR, or limit to OCR only, or Barcode Only.
    - Decoders: ability to capture any of Zebra supported decoders, previously only the default barcodes were supported.
  - Added support for postal codes (via camera or imager) in
    - Free-Form Image Capture (workflow Input) – Barcode Highlighting/Reporting
    - Barcode highlighting (Barcode Input).
 Postal Codes: US PostNet, US Planet, UK Postal, Japanese Postal, Australia Post, US4state FICS, US4state, Mailmark, Canadian postal, Dutch Postal, Finish Postal 4S.
  - Updated version of Decoder library IMGKIT\_9.02T01.27\_03 is added.
  - New Configurable Focus Parameters offered for devices with SE55 Scan Engine.

### ○ Resolved Issues

- Resolved Enable Touch Feedback.
- Resolved an issue with camera preview when COPE is enabled.
- Resolved an issue with decode audio feedback setting to none.
- Resolved issue with SE55 R07 firmware.
- Resolved an issue with scanning application getting frozen when switching from Guest mode to Owner mode.
- Resolved an issue with Picklist + OCR.
- Resolved an issue camera scanning.
- Resolved an issue with localization of Barcode highlighting in Datawedge.
- Resolved an issue with Document Capture template not getting displayed.
- Resolved an issue with parameters not visible in Device Central app for BT scanners.
- Resolved an issue with Picklist + OCR using Camera.
- Resolved an issue with pairing of BT scanner.

#### Usage Notes

- None

## Version Information

Below Table contains important information on versions

Description	Version
Product Build Number	14-20-14.00-UG-U160-STD-ATH-04
Android Version	14
Security Patch level	February 01, 2025
Component Versions	Please see Component Versions under Addendum section

## Device Support

The products supported in this release are TC22, TC27, TC53, TC58, TC73, TC78, HC20, HC50, ET60 and ET65 family of products.

Please see device compatibility details under Addendum Section.

## OS Update Installation Requirements and Instructions

- For devices TC53, TC58, TC73 and TC78 to update from A11 to this A14 release, user must follow below steps:
  - **Step-1:** Device **MUST** have A11 May 2023 LG BSP Image **11-21-27.00-RG-U00-STD** version or a greater A11 BSP version installed which is available on [zebra.com](https://zebra.com) portal.
  - **Step-2:** Upgrade to this release A14 BSP version **14-20-14.00-UG-U00-STD-ATH-04**. For more detailed instructions refer [A14 6490 OS update instructions](#)

- For devices TC22, TC27, HC20, HC50, TC53, TC58, TC73, TC78, ET60 and ET65 to update from A13 to this A14 release, user must follow below steps:
  - **Step-1:** Device can have any A13 BSP version installed which is available on [zebra.com](https://zebra.com) portal.
  - **Step-2:** Upgrade to this release A14 BSP version **14-20-14.00-UG-U00-STD-ATH-04**. For more detailed instructions refer [A14 6490 OS update instructions](#) .

## Known Constraints

- Limitation of Battery Stats in COPE mode.
- System settings access (Access ILMgr) - Reduced settings with Accessibility allows users to access application permissions, using Privacy Indicators.

## Important Links

- Installation and setup instructions – please refer below links.
  - [A14 6490 OS update instructions](#)
  - [Zebra Techdocs](#)
  - [Developer Portal](#)

## Addendum

### Device Compatibility

This software release has been approved for use on the following devices.

Device Family	Part Number	Device Specific Manuals and Guides
---------------	-------------	------------------------------------



TC53	TC5301-0T1E1B1000-A6 TC5301-0T1E4B1000-A6 TC5301-0T1E4B1000-IN TC5301-0T1E4B1000-NA TC5301-0T1E4B1000-TR TC5301-0T1E4B1N00-A6 TC5301-0T1E7B1000-A6 TC5301-0T1E7B1000-NA TC5301-0T1K4B1000-A6 TC5301-0T1K4B1000-NA TC5301-0T1K4B1B00-A6 TC5301-0T1K6B1000-A6 TC5301-0T1K6B1000-NA	TC5301-0T1K6B1000-TR TC5301-0T1K6E200A-A6 TC5301-0T1K6E200A-NA TC5301-0T1K6E200B-NA TC5301-0T1K6E200C-A6 TC5301-0T1K6E200D-NA TC5301-0T1K6E200E-A6 TC5301-0T1K6E200F-A6 TC5301-0T1K7B1000-A6 TC5301-0T1K7B1000-NA TC5301-0T1K7B1B00-A6 TC5301-0T1K7B1B00-NA TC5301-0T1K7B1N00-NA	<a href="#">TC53</a>
TC73	TC7301-0T1J1B1002-NA TC7301-0T1J1B1002-A6 TC7301-0T1J4B1000-A6 TC7301-0T1J4B1000-NA TC7301-0T1J4B1000-TR TC7301-0T1K1B1002-NA TC7301-0T1K1B1002-A6 TC7301-0T1K4B1000-A6 TC7301-0T1K4B1000-NA TC7301-0T1K4B1000-TR TC7301-0T1K4B1B00-NA TC7301-0T1K5E200A-A6 TC7301-0T1K5E200A-NA TC7301-0T1K5E200B-NA TC7301-0T1K5E200C-A6 TC7301-0T1K5E200D-NA TC7301-0T1K5E200E-A6 TC7301-0T1K5E200F-A6 TC7301-0T1K6B1000-FT TC7301-0T1K6B1002-A6	TC7301-0T1K6E200A-A6 TC7301-0T1K6E200A-NA TC7301-0T1K6E200B-NA TC7301-0T1K6E200C-A6 TC7301-0T1K6E200D-NA TC7301-0T1K6E200E-A6 TC7301-0T1K6E200F-A6 TC7301-3T1J4B1000-A6 TC7301-3T1J4B1000-NA TC7301-3T1K4B1000-A6 TC7301-3T1K4B1000-NA TC7301-3T1K5E200A-A6 TC7301-3T1K5E200A-NA TC73A1-3T1J4B1000-NA TC73A1-3T1K4B1000-NA TC73A1-3T1K5E200A-NA TC73B1-3T1J4B1000-A6 TC73B1-3T1K4B1000-A6 TC73B1-3T1K5E200A-A6	<a href="#">TC73</a>
TC58	TC58A1-3T1E4B1010-NA TC58A1-3T1E4B1E10-NA TC58A1-3T1E7B1010-NA TC58A1-3T1K4B1010-NA TC58A1-3T1K6B1010-NA TC58A1-3T1K6E2A1A-NA TC58A1-3T1K6E2A1B-NA TC58A1-3T1K6E2A8D-NA TC58A1-3T1K7B1010-NA TC58B1-3T1E1B1080-A6 TC58B1-3T1E4B1080-A6 TC58B1-3T1E4B1080-IN TC58B1-3T1E4B1080-TR TC58B1-3T1E4B1B80-A6 TC58B1-3T1E4B1N80-A6 TC58B1-3T1E6B1080-A6 TC58B1-3T1E6B1080-BR	TC58B1-3T1E6B1W80-A6 TC58B1-3T1K4B1080-A6 TC58B1-3T1K4B1E80-A6 TC58B1-3T1K6B1080-A6 TC58B1-3T1K6B1080-IN TC58B1-3T1K6B1080-TR TC58B1-3T1K6E2A8A-A6 TC58B1-3T1K6E2A8C-A6 TC58B1-3T1K6E2A8E-A6 TC58B1-3T1K6E2A8F-A6 TC58B1-3T1K6E2W8A-A6 TC58B1-3T1K6E2W8A-TR TC58B1-3T1K7B1080-A6 TC58B1-3T1K7B1E80-A6 TC58C1-3T1K6B1080-JP	<a href="#">TC58</a>

TC78	TC78A1-3T1J1B1012-NA TC78B1-3T1J1B1082-A6 TC78A1-3T1J4B1A10-FT TC78A1-3T1J4B1A10-NA TC78A1-3T1J6B1A10-NA TC78A1-3T1J6B1E10-NA TC78A1-3T1J6B1W10-NA TC78A1-3T1K1B1012-NA TC78B1-3T1K1B1082-A6 TC78A1-3T1K4B1A10-NA TC78A1-3T1K6B1A10-NA TC78A1-3T1K6B1B10-NA TC78A1-3T1K6B1E10-NA TC78A1-3T1K6B1G10-NA TC78A1-3T1K6B1W10-NA TC78A1-3T1K6E2A1A-FT TC78A1-3T1K6E2A1A-NA TC78A1-3T1K6E2A1B-NA TC78A1-3T1K6E2E1A-NA TC78B1-3T1J4B1A80-A6 TC78B1-3T1J4B1A80-IN TC78B1-3T1J4B1A80-TR	TC78B1-3T1J6B1A80-A6 TC78B1-3T1J6B1A80-TR TC78B1-3T1J6B1E80-A6 TC78B1-3T1J6B1W80-A6 TC78B1-3T1K4B1A80-A6 TC78B1-3T1K4B1A80-IN TC78B1-3T1K4B1A80-TR TC78B1-3T1K6B1A80-A6 TC78B1-3T1K6B1A80-IN TC78B1-3T1K6B1B80-A6 TC78B1-3T1K6B1E80-A6 TC78B1-3T1K6B1G80-A6 TC78B1-3T1K6B1W80-A6 TC78B1-3T1K6E2A8A-A6 TC78B1-3T1K6E2A8C-A6 TC78B1-3T1K6E2A8E-A6 TC78B1-3T1K6E2A8F-A6 TC78B1-3T1K6E2E8A-A6	<a href="#">TC78</a>
HC20	WLMT0-H20B6BCJ1-A6 WLMT0-H20B6BCJ1-TR WLMT0-H20B6DCJ1-FT WLMT0-H20B6DCJ1-NA		<a href="#">HC20</a>
HC50	WLMT0-H50D8BBK1-A6 WLMT0-H50D8BBK1-FT WLMT0-H50D8BBK1-NA WLMT0-H50D8BBK1-TR		<a href="#">HC50</a>
TC22	WLMT0-T22B6ABC2-A6 WLMT0-T22B6ABC2-FT WLMT0-T22B6ABC2-NA WLMT0-T22B6ABC2-TR WLMT0-T22B6ABE2-A6 WLMT0-T22B6ABE2-NA WLMT0-T22B6CBC2-A6	WLMT0-T22B6CBC2-NA WLMT0-T22B6CBE2-A6 WLMT0-T22B8ABC8-A6 WLMT0-T22B8ABD8-A6 WLMT0-T22B8ABD8-NA WLMT0-T22B8CBD8-A6 WLMT0-T22B8CBD8-NA WLMT0-T22D8ABE2-A601	<a href="#">TC22</a>
TC27	WCMTA-T27B6ABC2-FT WCMTA-T27B6ABC2-NA WCMTA-T27B6ABE2-NA WCMTA-T27B6CBC2-NA WCMTA-T27B8ABD8-NA WCMTA-T27B8CBD8-NA WCMTB-T27B6ABC2-A6 WCMTB-T27B6ABC2-BR	WCMTB-T27B8ABD8-A6 WCMTB-T27B8ABE8-A6 WCMTB-T27B8CBC8-BR WCMTB-T27B8CBD8-A6 WCMTD-T27B6ABC2-TR WCMTJ-T27B6ABC2-JP WCMTJ-T27B6ABE2-JP WCMTJ-T27B6CBC2-JP	<a href="#">TC27</a>

	WCMTB-T27B6ABC2-TR WCMTB-T27B6ABE2-A6 WCMTB-T27B6CBC2-A6 WCMTB-T27B6CBC2-BR WCMTB-T27B8ABC8-A6	WCMTJ-T27B8ABC8-JP WCMTJ-T27B8ABD8-JP	
ET60	ET60AW-0HQAGN00A0-A6 ET60AW-0HQAGN00A0-NA ET60AW-0HQAGN00A0-TR ET60AW-0SQAGN00A0-A6 ET60AW-0SQAGN00A0-NA ET60AW-0SQAGN00A0-TR ET60AW-0SQAGS00A0-A6	ET60AW-0SQAGS00A0-NA ET60AW-0SQAGS00A0-TR ET60AW-0SQAGSK0A0-A6 ET60AW-0SQAGSK0A0-NA ET60AW-0SQAGSK0A0-TR ET60AW-0SQAGSK0C0-A6 ET60AW-0SQAGSK0C0-NA	<a href="#">ET60</a>
ET65	ET65AW-ESQAGE00A0-A6 ET65AW-ESQAGE00A0-NA ET65AW-ESQAGE00A0-TR ET65AW-ESQAGS00A0-A6 ET65AW-ESQAGS00A0-NA ET65AW-ESQAGS00A0-TR	ET65AW-ESQAGSK0A0-A6 ET65AW-ESQAGSK0A0-NA ET65AW-ESQAGSK0A0-TR ET65AW-ESQAGSK0C0-A6 ET65AW-ESQAGSK0C0-NA	<a href="#">ET65</a>

## Component Versions

Component / Description	Version
Linux Kernel	5.4.274-qgki
AnalyticsMgr	10.0.0.1008
Android SDK Level	34
Audio (Microphone and Speaker)	0.9.0.0
Battery Manager	1.5.4
Bluetooth Pairing Utility	6.2
Zebra Camera App	2.5.8
DataWedge	15.0.16
Files	14-11531109
License Manager and LicenseMgrService	6.1.4 and 6.3.9
MXMF	14.1.0.3
NFC	PN7160_AR_11.02.00
OEM info	9.0.1.257
OSX	QCT6490.140.14.10.8
Rxlogger	14.0.12.21
Scanning Framework	43.13.1.7
StageNow	13.4.0.0
Zebra Device Manager	14.1.0.3
WLAN	FUSION_QA_4_1.2.0.005_U FW: 1.1.2.0.1258.1
WWAN Baseband version	Z240605A_039.3-00225
Zebra Bluetooth	14.5.0
Zebra Volume Control	3.0.0.111
Zebra Data Service	14.0.0.1032
Wireless Analyzer	WA_A_3_2.1.0.021_U

## Revision History

Rev	Description	Date
1.0	Initial release	December 1, 2024