



Zebra ZXP Series 3 Printer Driver

First Driver Release

DZ3CG.02.02.00

Readme File

This document contains information on the release of the ZXP Series 3 Microsoft Windows® Driver software, Version DZ3CG.02.02.00, as of 27th February, 2012. This is the third released driver version of the ZXP Series 3 printer.

Contents:

1. Supported OS platforms
2. Driver Install/Uninstall procedure
3. Enhancements in this driver version
4. Known issues with this driver version
5. Technical assistance contact information

Supported Configurations

This release of the driver is intended for installation and use with the following operating systems:

- Windows® XP
- Windows Vista® (32 and 64 bit)
- Windows Server® 2003
- Windows 7® (32 and 64 bit)
- Windows Server® 2008 (32 and 64 bit)



Microsoft Driver Support Matrix:

Supported Windows Drivers Microsoft OS ¹	One to One	One to Many	Many to One	Many to Many	Printer Pooling ²
	1 Printer - 1 Host	One Host - Many Printers	Multiple Hosts (Drivers) - One Printer	Multiple Hosts (Drivers) - Many Printers	
Server 2008 64Bit	Yes	Yes	Yes	Yes	Yes
Server 2008 32Bit	Yes	Yes	Yes	Yes	Yes
Server 2003	Yes	Yes	Yes	Yes	Yes
Windows 7 64 Bit	Yes	Yes	Yes	Yes	Yes
Windows 7 32 Bit	Yes	Yes	Yes	Yes	Yes
Vista 64 Bit³	Yes				
Vista 32 Bit²	Yes				
Windows XP	Yes	Yes	Yes	Yes	Yes

Client / Server Printer sharing support Matrix

The following Matrix shows the tested configurations between various Microsoft OS in a shared Client / Server print environment.

Printer Sharing Matrix	Windows OS Driver Clients		
	Win 7 32 Bit	Win 7 64 Bit	Windows XP
Windows OS server (Driver Host)			
Server 2003	Yes		Yes
Windows 7 64 Bit	Yes	Yes	Yes
Windows 7 32 Bit	Yes		Yes
Windows XP (All Editions) SP 2 and above			Yes

This software release is intended to be a common driver for installation and use with the following Zebra Card Printers and the associated firmware version, noted in the Table below:

Printer Models	Minimum firmware revision
ZXP Series 3	FZ3MG.01.03

¹ Driver installed on individual Client PC's

² Printer Pooling Sharing not supported.

³ Need to qualify Service Pack support



Driver Installation / Un-Installation Procedures

Steps for Installation:

1. Run the *DZ3CG.02.02.00.exe* from explorer or command prompt. This is the setup for the ZXP Series 3 printer driver.
Note: If installing the driver from the Driver CD, and the installation does not run automatically, launch the web browser. Within the browser, open the *index.htm* file at the top/root level of the CD. Choose the options on the CD to start installing the driver. Follow the on-screen prompts to complete the driver installation for your supported printer (listed above).
2. Choose among the Ethernet and USB printers. Based upon this, the printer drivers for the specific printers will be installed.
3. Choose the destination location or leave it to default value.
4. In case of Ethernet printer driver, a dialog will appear with available IP addresses or the option to input an IP address of the Ethernet printer. Enter the Ethernet printer IP address and click *Ok*. This will cause the Ethernet printer to be installed in the system.
5. After the installation is completed, *Zebra ZXP Series 3 Network Card Printer* will be displayed as printer name in case of Ethernet printers, and *Zebra ZXP Series 3 USB Card Printer* will be displayed in case of USB printers in *Control Panel -> Printers and Faxes*
6. Now the printer will be installed and ready to use.
7. Run any application like Zebra CardStudio, Microsoft Windows® WORD® or other Card Design application to perform printing.

Steps for Un-Installation:

1. In Add/Remove Programs, choose Zebra ZXP Series 3 Card Printer, click Remove. (Or), In Start Menu -> Programs ->Zebra ZXP Series 3 Card Printer, click Uninstall.
2. Choose Remove option.
3. A warning message will appear. Click Ok to confirm un-installation.
4. Reboot the system after the driver un-installation is complete.

Enhancements in Version DZ3CG.02.02.00

- Improve the monochrome image quality when using monochrome ribbons.

Known Issues in Current Version DZ3CG.02.02.00

- In a printer sharing configuration, the following combinations are not supported:



1. Windows Vista® client to Vista® host
 2. Windows Vista® client to Windows® XP, Windows Server® 2003, Windows Server® 2008, or Windows 7® hosts
 3. Windows 7® clients to Windows® XP host
- When printing over Ethernet using CardStudio R1.01.02 with the Job Log enabled, the printer will hang after a few printed cards. CardStudio must be closed, the spooler restarted, and the printer power cycled in order to recover from the failure.
 - For the KdO ribbon, the color adjustment preview image is not updated.

Technical Assistance:

For questions relating to the operation of Zebra equipment you already own, contact your reseller first. Alternately, contact Zebra Technical Support by using one of the following methods:

Technical Support Phone: 1-877-ASK-ZEBRA (1 877 275 9327).

Zebra Technologies Corporation
333 Corporate Woods Parkway
Vernon Hills, IL 60061-3109

You can also visit us on the web at <http://www.zebra.com/>