

OMNII XT15ni – NON-INCENDIVE HAND-HELD COMPUTER

IMPORTANT SAFETY & REGULATORY INFORMATION

The Omnii XT15ni (non-incendive) Hand-Held Computer has been qualified by UL LLC to the requirements of the USA and Canada for use in Class I, Division 2-Groups A, B, C and D T6 environments.

The users of this product are cautioned to use accessories and peripherals approved by Psion Inc. The use of accessories other than those recommended, or changes to this product that are not approved by Psion Inc., may void the compliance of this product and may result in the loss of the user's authority to operate the equipment.

Warnings & Cautions



Caution: This mark indicates that the user should read all included documentation before use.

Attention: Ce marquage indique que l'utilisateur doit, avant l'utilisation, lire toute la documentation incluse.



Warning: Explosion Hazard-Substitution of components may impair suitability for Class I, Division 2 locations.

Warning: This unit has **NO OPERATOR REPLACEABLE PARTS** other than the battery pack. Disassembly/assembly of the Omnii XT15ni must be performed by trained Psion service personnel at a Psion service depot. No unauthorized substitution of parts is allowed for the Omnii XT15ni hand-held.

Warning: Use **ONLY** the Psion Model ST3001-NI battery pack in the Omnii XT15ni. No substitutions are permitted without authorization from Psion personnel.

Warning: **DO NOT CHARGE OR CHANGE BATTERIES** in an area that is known to be hazardous. Replace batteries in an area known to be non-hazardous.

Warning: **EXPLOSION HAZARD. DO NOT REMOVE OR REPLACE LAMPS, FUSES OR PLUG-IN MODULES (AS APPLICABLE) UNLESS POWER HAS BEEN DISCONNECTED OR THE AREA IS KNOWN TO BE FREE OF IGNITIBLE CONCENTRATIONS OF FLAMMABLE GASES OR VAPORS.**

Warning: **EXPLOSION HAZARD. DO NOT DISCONNECT WHILE THE CIRCUIT IS LIVE UNLESS THE AREA IS KNOWN TO BE FREE OF IGNITIBLE CONCENTRATIONS.**

Warning: Exposure to some chemicals may degrade the sealing properties of materials used in the following devices: battery packs, housings, LCDs, touchscreens, keypads.

Replacement of modules, housings, keypads, LCDs or touchscreens, end-caps, pods or external connectors must only be performed at an authorized Psion service centre.



Caution: The battery pack used in this device may present a fire or chemical burn hazard if mistreated. Do not disassemble, heat above 100°C (+212°F) or incinerate. Dispose of used battery packs promptly. Keep away from children.

Caution: The following additional warnings and cautions must be observed for the safety of the operator and others in potentially hazardous locations:

The Omnii XT15ni must only be used when the ambient temperature is between -20°C and +50°C (-4°F and +122°F).

The Omnii XT15ni may **NOT** be connected to any of its available accessories while in potentially hazardous locations. This includes anything that uses the communications docking connector, headset, or microphone jacks. All allowed connections must be made while outside of the potentially hazardous location.

The use of Compact Flash, Secure Digital, and SIM Cards in the Omnii XT15ni while in potentially hazardous locations is permitted as long as these cards are not removed or changed while in the hazardous location.

Any connector cover removed while in ordinary locations must be reinstalled before entering a potentially hazardous location.



Battery Information

Caution: *The battery pack used in this device may ignite, create a chemical burn hazard, explode, or release toxic materials if mistreated. Do not incinerate, disassemble, or heat above 100°C (212°F). Charge ONLY with Psion Model ST3001-NI. Do not short circuit; may cause burns. Keep away from children.*

Use ONLY Psion battery pack Model ST3001-NI. Risk of fire or explosion if incorrect battery pack is used. Promptly dispose of used battery pack according to the instructions.

Attention: *Le bloc-piles utilisé dans cet appareil peut prendre feu, constituer un risque de brûlure chimique, exploser ou dégager des substances toxiques s'il est manipulé de façon inappropriée. Ne pas jeter au feu, démonter ou chauffer à plus de 100°C (212°F). Ne charger qu'avec les dispositifs Psion ST3001-NI. Ne pas court-circuiter; cela pourrait causer des brûlures. Garder hors de la portée des enfants.*

N'utiliser que le modèle de bloc-piles Psion ST3001-NI. L'utilisation d'un mauvais bloc-piles pourrait constituer un risque d'incendie ou d'explosion. Mettre rapidement au rebut tout bloc-piles utilisé, conformément aux instructions.

COMPANY HEADQUARTERS

Psion Inc.
2100 Meadowvale Boulevard, Mississauga
Ontario, Canada L5N 7J9
Tel: +1 905 813 9900
Fax: +1 905 812 6300

SUPPORT SERVICES

For local support services, go to:
<http://www.pSION.com/service-and-support.htm>