

Release Notes - MC32N0 CE 7.0 Standard Rev C2 – 10.57.04

[Introduction](#)
[Description](#)
[Contents](#)
[Device Compatibility](#)
[Installation Requirements](#)
[Installation Instructions](#)
[Part Number and Release Date](#)

Introduction

MC32N0 is Enhanced Mid-range, Industrial-grade Rugged Handheld.

Main features:

- Affordable lightweight rugged mobile computing for key-based applications; Multiple field proven form factors; Gun;
- Compatibility with the MC3000 accessory ecosystem

Device Specifications:

- 800MHz Dual Core Processor
- 512MB RAM/2GB Flash memory
- CE7.0
- 3" Color display
- 802.11 a/b/g/n
- SE4750
- IP54 sealing
- 5" Drop to concrete at room
- 500 ½ meter Tumble
- New, improved battery installation and removal experience

OSUpdate Package 10.57.04 contains the SW required to update a MC32N0 CE 7.0 device to the RevC software.

Description

- OS - Windows CE 7.0 (07.00.2824)
- QFE - Feb2016_Build2866_Uptd56
- Fusion Radio SW Version 2.03.0.0.012R (FCC compliant & Support for IEEE 802.11r-Fast Transition)
- RD Client Version 7.08.77
- DataWedge Version 3_7_16_151009
- TelnetCE Version 7.3.239
- emScript Version 1.3.11
- CaptureDump Version 3.2.2
- B2MClient (Elemex Version 1.0.0.381). Can be installed using \Windows\Elemex.cab
- Asset Tracker Lite Version1.0

SPR FIXES

- SPR 26260 - Resolved an issue where touch panel does not disable when its power state is set to D4
- SPR 27748 - Memory improvements in scanner module
- SPR 28621 - Resolved an issue where registry is not merging if semicolon is present in the path
- SPR 26471 - Resolved an issue where Kiosk mode/full screen mode is not working in IE
- SPR 27387 - Resolved an issue where IE-checkbox control does not render
- SPR 27341 - Resolved an issue in DataWedge where backslash in barcode does not work
- SPR 28406 - Added support for NLS
- SPR 27173 - Resolved an issue where code page encodings in IE was missing
- SPR 28299 - Resolved an issue where "Add to Favorites" option missing from Favorites file menu in IE
- SPR 26489 - Resolved an issue whereby audio being played out the headset for a short period of time when resuming from suspend
- SPR 28982 - Resolved an issue where frmMain_Activated event was not triggered
- SPR 28140 - Added support for MC32 in eMscript
- SPR 28478 - Resolved an issue where device loses ethernet connection after swapping to different slots in ethernet cradle
- SPR 28952 - Resolved an issue where bluetooth headset audio stability issues were seen with TekSpeech Pro
- SPR 29299 - Resolved an issue where calibration data is not retained after warm boot
- SPR 29609 - Resolved an issue where msmq dlls was not compatible with CE7

Optional Hotfixes

The following SPR fixes are available as HotFixes which can be applied on top of this release

- SPR 28950 - MC32N0-RL4HCHEIA - Application hangs on SCAN_Enable
- SPR 28536 - On Windows 10, when \Application is mounted as removable storage, file operations takes a very long time

Notes

To enable IE KIOSK feature reset the below registry keys to 0

```
[HKEY_CURRENT_USER\Software\Microsoft\Internet Explorer\Main]
"Task Bar"=dword:00000000
"Status"=dword:00000000
"Command Bar"=dword:00000000
"Animation"=dword:00000000
"Menu Bar"=dword:00000000
"URL"=dword:00000000
```

Contents

- 32N0c70BenUP105704.zip - OSUpdate Package
- 32N0c70BenUC105704.zip - OSUpdate Package with Clean application
- 32N0c70BenAB105704.APF - Airbeam Package
- 32N0c70BenAC105704.APF - Airbeam Package with Clean application
- 32N0c70BenOS105704.hex -OS Hex file

Device Compatibility

This software release has been approved for use with the following Symbol devices.

| Device | SKUs |
|--------|-------------------|
| MC32N0 | MC32N0-GI2HCLE0A |
| | MC32N0-GI3HCLE0A |
| | MC32N0-GI4HCLE0A |
| | MC32N0-GL2HCLE0A |
| | MC32N0-GL3HCLE0A |
| | MC32N0-GL4HCLE0A |
| | MC32N0-RL2HCLE0A |
| | MC32N0-RL2SCLC0A |
| | MC32N0-RL2SCLE0A |
| | MC32N0-RL2SCLK0A |
| | MC32N0-RL3HCLE0A |
| | MC32N0-RL3SCLC0A |
| | MC32N0-RL3SCLE0A |
| | MC32N0-RL4SCLE0A |
| | MC32N0-SI2HCLE0A |
| | MC32N0-SI2SCLE0A |
| | MC32N0-SI3HCLE0A |
| | MC32N0-SI4HCLE0A |
| | MC32N0-SI4SCLE0A |
| | MC32N0-SL2HCLE0A |
| | MC32N0-SL2HCLE0TN |
| | MC32N0-SL2SCLE0A |
| | MC32N0-SL3HCLE0A |
| | MC32N0-SL4HCLE0A |

Installation Requirements

MC32N0 device must contain a released version of CE 7.0 Software

Installation Instructions

- Unzip ZIP file and copy its content (OSUpdate folder) to the \Storage Card folder
- Place the SD card in the device to be upgraded
- Place the device to be upgraded on A/C power supply.
- Navigate to the \Storage Card\OSUpdate and invoke the 32N0c70Ben_SD shortcut

OR

- Unzip ZIP file and copy its content (OSUpdate folder) to the \temp folder
- Place the device to be upgraded on A/C power supply.
- Navigate to the \temp\OSUpdate folder and invoke the 32N0c70Ben_TEMP shortcut

Part Number and Release Date

32N0c70BenUP105704
32N0c70BenUC105704
32N0c70BenAB105704
32N0c70BenAC105704
32N0c70BenOS105704

July 14, 2016