
Release Notes - <ET1N0 JB Reset Packages>

- [Introduction](#)
 - [Description](#)
 - [Contents](#)
 - [Device Compatibility](#)
 - [Installation Requirements](#)
 - [Installation Instructions](#)
 - [Part Number and Release Date](#)
-

Introduction

These packages will put the terminal into default factory settings.

Description

1. The ET1N0JXXFR0000001.zip contains Recovery package to perform factory reset on the terminal.
2. The ET1N0JXXER0000001.zip contains Recovery package to perform factory reset on the terminal and it will not erase the Enterprise folder.

Contents

1. ET1N0JXXFR0000001.zip – Factory Reset Package
2. ET1N0JXXER0000001.zip – Enterprise Reset Package

Device Compatibility

This software release has been approved for use with the following devices.

Device Part Number	Operating System
ET1N0	Android v4.1.1 Jelly Bean

Installation Requirements

- ET1N0 device must be running with Android v4.1.1 Jelly Bean operating system

Installation Instructions

Steps:

1. Copy reset package zip file to the root directory of SD card
2. Place the SD card in the device to be upgraded and connect to A/C power
3. Press and hold the Power button on the device until the Device options menu appears
4. Tap on Reset to reboot the device
5. When the device is rebooting hold the right Scan/Action button to enter Recovery update mode
6. When the Recovery Mode screen appears release the Right Scan/Action button.
7. Tap Home Key to access recovery menu screen
8. Tap P1, P2 keys to navigate to “apply update from /sdcard” option
9. Tap P3 to select this option
10. Tap P1, P2 keys to navigate to the reset zip file
11. Tap P3 to select this option
12. After pressing P3, the reset process will start.
13. After completing successfully, the screen will be back to Recovery menu
14. Tap P1, P2 keys to navigate to "reboot system now" option
15. Tap P3 to select this option
16. After pressing P3 system will reboot and device will enter Android system.

Please do not remove the device from A/C power during this time.

Part Number and Release Date

ET1N0JXXFR0000001
ET1N0JXXER0000001

