

Release Notes – Zebra Android Oreo 01-21-18.00-ON-U00-STD Release (AOSP) - China Only

Description

The details of the Android AOSP Oreo release 01-21-18.00-ON-U00-STD that covers family of products including TC52, TC57, TC72, TC77, TC52HC, PS20x, TC8300, VC8300, MC9300, L10A, and CC600, CC6000. Please see, Device Compatibility under Addendum Section for more details.

Software Packages

Package Name	Description
HE_FULL_UPDATE_01-21-18.00-ON-U00-STD.zip	Full Package Update
HE_DELTA_UPDATE_01-18-02.00-ON_TO_01-21-18.U00-ON.ZIP	Delta Package Update

Security Updates

This build is Compliant up to [Android Security Bulletin](#) of July 01 2019.

New Features

- Added Support for Launch of New products EC30 and L10A.
- Added Support for Various TC8300 (DPM, DPM wide Angle) SKU
- Added Support for Various MC9300 (Freezer and 34,43, 58, 29, 53 Keys) SKU
- Added soft PTT buttons for PTT-Express for devices with no Keys (Example Kiosk)
- Added capability to use Single Barcode Staging with SUW Bypass
- Added Single Barcode Staging with SUW Bypass (OSx) Note: *.bin for MX 9.1 above needs to be generated from latest StageNow tool with MX 9.1 and above only*
- Added support and Interface for Configuring HW vs SW WakeUp Sources
- Added Support for Keyboard Audible feedback, NFC, Vibrator, Camera for MC9300.
- Added New APK to quickly access display Densities and Font scaling and a power menu short cut which allows it to be launched when extended power menu option is enabled through developer options
- Added EC30 Locking Cradle Support has being added. This also includes a demo Application on the device that supports Unlocking as well as running specific diagnostic tests with device in cradle
- Added support for Scan and Pair by pressing hardware scan trigger when in the Device Central app's main screen.
- Added support for new Bluetooth Scanners: DS2278, DS8178
- Added Voice trigger support for [DataWedge](#)

- Added SE4750 DPM support in [EMDK](#)
- Added Controlling HW (Enable / Disable) wakeup sources
- Added "Never" option to Display Sleep mode for Kiosk devices
- WLAN
 - Added Coverage View in [WorryFree WiFi](#) (WFW).
 - Added CCXv4 Compliance.
 - WLAN Soft AP Certification
- WAN Specific (Not Applicable for WLAN only devices)
 - Added support for Sprint Curiosity SIMs

Fixes

- Fixed: SPR36661/37083, where PS20 terminals were not able to communicate to the cradles after the cradles were rebooted
- Fixed: SPR 36514 (PS20) where apps were being killed due to heavy CPU usage on device
- Fixed: SPR-36925 wherein scanner was not available for second app when an ANR or crash occurred on the first app
- Fixed: SPR37124 –where in ADF rule with crunch spaces was removing last character from barcode data with space.
- Fixed: SPR37060 wherein Datawedge was not disabling the scanner upon resume during app transition from background to foreground causing intermittent scanning failures

Version Information

Below Table contains important information on versions

Description	Version
Product Build Number	01-21-18.00-ON-U00-STD
Android Version	8.1.0
Security Patch level	July 1, 2019
Linux Kernel	4.4.78
Component Versions	Please see Component Version under Addendum section

Installation

Requirements and Instructions

https://www.zebra.com/content/dam/zebra_new_ia/en-us/software/operating-system/helios/oreo-os-update-instructions.pdf

Upgrade options

Below table provides detailed information on shortest path to upgrade based on current version of software.

Current Software Version on Device	Steps to get to this Release	Comments
01-13-20.00-ON-Uxx	Apply Full Package Update HE_FULL_UPDATE_01-21-18.00-ON-U00-STD.zip	
01-18-02.00-ON-Uxx	<p>Option 1: Apply Delta Package Update HE_DELTA_UPDATE_01-18-02.00-ON_TO_01-21-18.U00-ON</p> <p>Option 2: Full Package Update Apply HE_FULL_UPDATE_01-21-18.00-ON-U00-STD.zip</p>	Option #1 is recommended as size of Delta package update is smaller compared to Full Package Update

Known Constraints

Below are Known Constraints and workaround if applicable.

- WiFi sleep policy set to "Always" (Android O limitation)
- "Get Status for all Wake-Up sources" is returning "Enabled" when all Wake-up sources are disabled
- "Feature not supported" staging error message comes after staging enable wake up source function via stagenow, even though operation is successful.
- Some devices operate at 320 dpi. This screen configuration results in the majority of the AOSP applications displaying content consistently in both portrait and landscape modes. In most cases if the application layout is not optimal in landscape it is optimal in portrait or vice versa. However there are a few applications that do not render properly in either portrait or landscape. In this case the suggested alternative is to change the display size using the bundled Display Settings APK or use settings menu to change the display size and font size (settings > Display > Advanced settings > Display Size / Font Size).

Addendum

Device Compatibility

This software release has been approved for use on the following devices.

Device Family	Part Number	Product Specific Manual
TC52	TC520K-2PEZU4P-CN TC520K-2PEZU4P-CN TC520K-2HEZU4P-CN	Visit Manuals Section under TC52 Home Page
TC72	TC720L-0ME24B0-CN	Visit Manuals Section under TC72 Home Page
PS20	PS20J-B2G2CN00 PS20J-P4G2CN00	Visit Manuals Section under PS20 Home Page
TC77		Visit Manuals Section under TC77 Home Page
TC57		Visit Manuals Section under TC57 Home Page
CC600		
CC6000		
TC8300		
MC9300	MC930B-GSEEG4CN MC930B-GSCDG4CN MC930B-GSEDG4CN MC930B-GSADG4CN MC930B-GSACG4CN MC930P-GFADG4CN MC930P-GFCDG4CN MC930P-GFEDG4CN	Visit Manuals Section under MC93 Home Page
L10AW	RTL10B1-xxAxxX0x00CN (China) <i>Note: 'x' Stands for wild card for different configurations.</i>	

Component Version

Functional Area	Versions
ActiveEdge	2.5.16
AnalyticsMgr	2.4.0.1251
Audio (Microphone and Speaker)	0.41.0.0
Battery Management	Version : 1.4.2
Battery Swap (Enhanced)	Version : 2.2.0
Bluetooth Pairing Utility	Version 3.16
Data Analytics	3.5.0.1177
DataWedge	7.4.44
Device Central	2.1.0.9
Diagnostic Tool	v1.18.0.3
EMDK	7.4.20.2420
Enterprise Keyboard	2.2.2.1
Fota	1.0.0.6
License Manager and License Agent	version 3.2.0 and version 3.2.0.3.2.0
MSRN	2.01
MX	MXMF version:9.1.1.32
NFC	NFC_NCIHALx_ARC0.8.4.0
OSX	QCT.81.8.16.7
PTT Express	3.1.42
Rxlogger and RxLoggerUtility	Version 5.4.16.0 and Version: 1.3.3.11
Scanning Framework	22.1.21.0
Simulscan	Version: 3.0.6 SimulScanEngine: 2.0.9
WorryFree Wifi Analyzer (WFW / SmartMU)	WFW_QA_2_3.6.0.006_O
StageNow	3.4.1.4
Touch Panel	2.0-Finger-1-0 for Thunder
WLAN	FUSION_QA_2_1.6.0.011_O
Zebra BlueTooth	1.0
Zebra Data Service	3.5.0.1177
Zebra Volume Control (ZVC)	2.2.0.5
Zebra Folders	9.1

Revision History

REV	DESCRIPTION	DATE
1.0	Initial Release	July 24, 2019