



MC92N0 PREMIUM OPERATING SYSTEM WITHOUT MS OFFICE BSP 05.57.17 RELEASE NOTES

INTRODUCTION

The MC92N0G is Symbol's Premium industrial rugged handheld for inpremise scan intensive applications and is the next evolution of the MC9190G product – the best selling rugged mobile computer in the industry designed for such markets as retail, manufacturing, wholesale distribution and thirdparty logistics where intensive bar-code scanning takes place. The MC92N0G is a true systemslevel mobility solution, not just a mobile computer. The solution encompasses not only the new MC92N0G itself, but also software tools, accessories/peripherals and mobility services to provide a true endtoend solution.

Update Loader Image v05.57.17 contains the SW required to update a MC92N0-G Premium device having v14.57.07 or earlier versions and v10.55.11.

DESCRIPTION

1. Operating System: WEHH 6.5.3 AKU 29366
2. CPU Speed OMAP4430 ES2.3 - 1 GHz
3. Flash eMMC- 2GB
4. RAM - SDRAM - LPDDR2 1GB
6. Bluetooth: StoneStreetOne: BT Explorer 2.1.1 Build 28342
7. IST FW 1.13.0
8. PTT/Team Express v1.1.71.0000
9. Fusion Radio SW Version 2.03.0.0.012R (FCC compliant & Support for IEEE 802.11r-Fast Transition)
10. DataWedge v3.7.16
11. B2MClient (Elemesz Version 1.0.0.381).It can be installed using \\Windows\\Elemesz.cab



12. eMscript version 1.3.11

13. Capture Dump version 3.2.2

General Enhancements

1. Support for SE4850 Extended Range Imager
2. External Agent - v2.57

3. PTT without having a wired or BT headset is no longer supported on MC92 units shipped from factory after July 1, 2016 because microphone was removed.

SPR Fixes

1. SPR 30104 - Resolved a display flickering issue observed during manufacturing

Notes

- Microsoft Office will not be available in this release.
- SPR 24711:RF Apps performance can be improved by setting the below registry key for the specific <Nic Adapter Name> like XWING, SMSC9500, RndisFn, AsyncMac, PPTP, L2TP, PPPOE, LANNDS
`[HKEY_LOCAL_MACHINE\Comm\<NIC Adapter Name>\Parms\Tcpip]
"TcpAckFrequency"=dword:1`

CONTENTS

92N0w65LenUL055717.zip	OSUpdate Package without Clean Application
92N0w65LenUC055717.zip	OSUpdate Package with Clean Application
92N0w65LenAB055717.apf	AirBeam Package without Clean Application
92N0w65LenAC055717.apf	AirBeam Package with Clean Application

DEVICE COMPATIBILITY

This software release has been approved for use with the following Symbol devices.

DEVICE	OPERATING SYSTEM
MC92N0	MICROSOFT WEHH 6.5 CLASSIC PREMIUM (WITHOUT MICROSOFT OF



INSTALLATION REQUIREMENTS

MC92N0 device must contain released version of Microsoft WEHH 6.5 Classic Premium Software.

INSTALLATION INSTRUCTIONS

1. Unzip the Update Loader Package (i.e 92N0w65LenUL055717.zip/92N0w65LenUC055717.zip) and copy its content to the \Storage Card folder.
2. Place the SD card in the device to be upgraded.
3. Place the device to be upgraded on A/C power supply.
4. Navigate to the \Storage Card folder and invoke the StartUpdLdr.exe.
5. The update will take about 3-4 minutes to complete. Please do not remove the device from A/C power during this time.

OR

1. Unzip the Update Loader Package (i.e 92N0w65LenUL055717.zip/92N0w65LenUC055717.zip) and copy its content to the \Temp folder.
2. Place the device to be upgraded on A/C power supply.
3. Navigate to the \Temp folder and invoke the StartUpdLdr.exe.
4. The update will take about 3-4 minutes to complete. Please do not remove the device from A/C power during this time.

PART NUMBER AND RELEASE DATE

92N0w65LenUL055717

92N0w65LenUC055717

92N0w65LenAB055717

92N0w65LenAC055717

November 14, 2016