



SEE MORE. DO MORE.



ZEBRA[®] Linux[®] Driver Specifications for ZXP Series 3[™] and ZXP Series 1[™] Card Printers



The Zebra ZXP Series 3 and ZXP Series 1 Linux driver enables high-quality card printing in the Linux software environment. Customers requiring a Linux driver can now enjoy a fully functional Common Unix Print System (CUPS) compatible print driver, which includes a core set of printer control functions that can be easily installed, tested and deployed for Linux-based enterprise card application deployments.

Highlighted Features

- Printer USB Plug-In-Play (PNP)
- Graphic UI-based installer and uninstaller support
- Silent mode installation and uninstallation for non-GUI based OS deployments
- Zebra card printer support for CUPS 1.4 or higher
- Network or full USB 2.0 printer support (2.0 only)
- 32-bit and 64-bit Linux OS
- Zebra printer error handling support
- Independent JAVA Card SDK

Linux Platform Distribution Support

- Zebra ZXP Series 1 and ZXP Series 3 printer driver for Red Hat (RHEL) Linux support:
 - Red Hat Enterprise Linux 6.5 32 bit
 - Red Hat Enterprise Linux 6.5 64 bit
- Zebra ZXP Series 1 and ZXP Series 3 printer driver for Ubuntu Linux support:
 - Ubuntu 12.04 (32 bit and 64 bit)
 - Ubuntu 13.04 and 13.10 (32 and 64 bit)
 - Ubuntu 14.04 (32 bit and 64 bit)



Supported Features

- Printer Properties Definition (PPD) based basic settings and configurations (CUPS PPD based UI)
- Zebra printer properties page
- YMCK front/K back ribbon combination supported
- Zebra Linux graphic user interface installer
- Card print orientation: portrait/landscape
- Select single-side or dual-side print
- Magnetic encoding functionality (default macro processing only)
- K (black) panel
- Full overlay varnish
- Number of copies
- CUPS print test card
- Printing mode

Supported Ribbon Media

	ZXP Series 3	ZXP Series 1
YMCKO	✓	✓
YMCKOK	✓	
KdO	✓	
KrO	✓	
Monochrome	✓	✓
K Resin	✓	
½ YMCKOKO*	✓	
½ YMCKO*	✓	
⅓ YMCKOKO*	✓	

* Contact your Zebra representative to determine Linux Driver media support and add custom feature capabilities.



SEE MORE. DO MORE.



Other Features

	ZXP Series 3	ZXP Series 1
Magnetic Stripe Encoding Support	✓	✓
Card Feeder Control	✓	✓
CUPS Web Admin Support (Port 631)	✓	✓
Print Test Cards via CUPS (Port 631)	✓	✓
Standard Test Card Print	✓	✓
Printer Parameters Card Print	✓	✓
Firmware Support	✓	✓
PRN File Support	✓	✓
Save & Restore	✓	✓
Cleaning	✓	✓

Printer Features/Options Not Supported in ZXP Series 3 and ZXP Series 1 Linux Driver

- Smart card encoding (contact and contactless)
- Laminating printers option
- Network printer sharing and printer pooling
- Advanced printer security features (including data encryption and printer host authentication)
- Media (ribbon types) not currently listed
- Image control support
- Defined and undefined K panel printing



Driver Features Not Available in Linux

- Bi-directional printer properties GUI
- Device information page
- Zebra Linux printer 'About' option
- Media information page
- Print front image on back
- Printer cleaning commands
- Image control functionality
- Resume print job error handling
- Printer parameters card print
- Black panel optimization
- Job log

Supported Modules and File Paths Fused in the Linux CUPS Printer Driver

Modules	Path
CUPS Filter	/usr/lib/cups/filter/ rastertozxp3
CUPS USB Backend	/usr/lib/cups/backend/zxp3usb
CUPS Socket Backend	/usr/lib/cups/backend/zxp3socket
CUPS PPD	/usr/share/cups/model/ZebraZXP3<>Printer.ppd
Udev Zebra ZXP3 PnP Binary	/lib/udev/ ZXP3-USB-Printer-Installer
Udev Rules	/lib/udev/20-ZebraZXP3Series.rules
Udev Rules	/lib/udev/70-ZebraZXP3Series.rules
Udev Rules	/lib/udev/zebrazxp3.rules
Zebra Printer Driver Installation Folder	/usr/local/ZebraZXP3Driver
MIME Type	/usr/share/cups/mime/pstozxp3ps.convs
Error Handling Binary	/usr/bin/ ZXP3ErrorNotify



Corporate Headquarters
+1 800 423 0442
inquiry4@zebra.com

Asia-Pacific Headquarters
+65 6858 0722
apacchannelmarketing@zebra.com

EMEA Headquarters
+44 (0)1628 556000
mseurope@zebra.com

Latin America Headquarters
+1 847 955 2283
inquiry4@zebra.com

Other Locations / USA: California, Georgia, Illinois, Rhode Island, Texas, Wisconsin **Europe:** France, Germany, Italy, the Netherlands, Poland, Spain, Sweden, Turkey, United Kingdom **Asia Pacific:** Australia, China, Hong Kong, India, Indonesia, Japan, Malaysia, Philippines, Singapore, South Korea, Taiwan, Thailand, Vietnam **Latin America:** Argentina, Brazil, Colombia, Florida (LA Headquarters in USA), Mexico **Africa/Middle East:** Dubai, South Africa

SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE

©2015 ZIH Corp. Zebra, the Zebra head graphic and Zebra Technologies logo are trademarks of ZIH Corp, registered in many jurisdictions worldwide. All product names and numbers are Zebra trademarks. All rights reserved. All other trademarks are the property of their respective owners.

(2/15)