

---

# **MC55E0 v02.57.00 WEHH 6.5 Classic Release Notes**

---

[Introduction](#)

[Description](#)

[General Enhancements](#)

[Contents](#)

[Device Compatibility](#)

[Installation Requirements](#)

[Installation Instructions](#)

[Part Number and Release Date](#)

---

## **Introduction**

With the MC55E0 Series, managers and task workers who spend their days inside your company walls have everything they need to take instant action, anywhere in your facility — indoors and outside. When it comes to meeting the needs of your workforce, the MC55E0 excels, offering the right level of features, the right level of rugged design and support for the most demanding business applications. The result? Workers in retail, hospitality, manufacturing, healthcare and government agencies can complete more tasks more accurately in less time, improving productivity and customer care. And with healthcare friendly colors, MC55E0-HC brings mobility to point-of-care applications, helping nurses and other caregivers eliminate errors at the patient bedside to improve the quality of care — and the patient experience

## **Description**

Update Loader Image 02.57.00 contains the Software required to flash an MC55E0 device with Rev B software release.

- WEHH 6.5 Professional AKU 29377
- FPGA ver. 2.19
- SOTI MobiStage client version v12.4.0 (Build-1045)
- DDT Tool v1.3.9
- UNIFIED\_SCANNER\_VER\_9
- Data Wedge v3.7.16

## **General Enhancements in 02.57.00:**

- Fusion Software X\_2.03.0.0.024R

Updated MC55E0 with latest regulatory rules

## **Contents**

<b>Files</b>	<b>Description</b>
55X0w65HcpUL025700.zip	OS update package (without clean application) Simplified Chinese
55X0w65HcpUC025700.zip	OS update package (with Clean Application) Simplified Chinese
55X0w65HcpAC025700.APF	AirBeam Package for OS update (with Clean Application) Simplified Chinese
55X0w65HcpAB025700.APF	AirBeam Package for OS update (without clean application) Simplified Chinese
55X0w65HctUL025700.zip	OS update package (without clean application) Traditional Chinese
55X0w65HctUC025700.zip	OS update package (with Clean Application) Traditional Chinese
55X0w65HctAC025700.APF	AirBeam Package for OS update (with Clean Application) Traditional Chinese
55X0w65HctAB025700.APF	AirBeam Package for OS update (without clean application) Traditional Chinese
55X0w65HkoUL025700.zip	OS update package (without clean application) Korean
55X0w65HkoUC025700.zip	OS update package (with Clean Application) Korean
55X0w65HkoAC025700.APF	AirBeam Package for OS update (with Clean Application) Korean
55X0w65HkoAB025700.APF	AirBeam Package for OS update (without clean application) Korean
55X0w65HsiUL025700.zip	OS update package (without clean application) Spanish
55X0w65HsiUC025700.zip	OS update package (with Clean Application) Spanish
55X0w65HsiAC025700.APF	AirBeam Package for OS update (with Clean Application) Spanish
55X0w65HsiAB025700.APF	AirBeam Package for OS update (without clean application) Spanish
55X0w65HitUL025700.zip	OS update package (without clean application) Italian
55X0w65HitUC025700.zip	OS update package (with Clean Application) Italian
55X0w65HitAC025700.APF	AirBeam Package for OS update (with Clean Application) Italian

55X0w65HitAB025700.APF	AirBeam Package for OS update (without clean application) Italian
55X0w65HfrUL025700.zip	OS update package (without clean application) French
55X0w65HfrUC025700.zip	OS update package (with Clean Application) French
55X0w65HfrAC025700.APF	AirBeam Package for OS update (with Clean Application) French
55X0w65HfrAB025700.APF	AirBeam Package for OS update (without clean application) French
55X0w65HdeUL025700.zip	OS update package (without clean application) German
55X0w65HdeUC025700.zip	OS update package (with Clean Application) German
55X0w65HdeAC025700.APF	AirBeam Package for OS update (with Clean Application) German
55X0w65HdeAB025700.APF	AirBeam Package for OS update (without clean application) German
55X0w65HjpUL025700.zip	OS update package (without clean application) Japanese
55X0w65HjpUC025700.zip	OS update package (with Clean Application) Japanese
55X0w65HjpAB025700.apf	AirBeam Package for OS update (without clean application) Japanese
55X0w65HjpAC025700.apf	AirBeam Package for OS update (with Clean Application) Japanese

## Device Compatibility

This software release has been approved for use with the following Zebra devices.

Device	Operating System
MC55E0	Microsoft WEHH 6.5 Professional

## Installation Requirements

MC55E0 device must contain a released version of Microsoft WEHH 6.5 Professional

## Installation Instructions

### Update Loader Package:

**Standard Update Procedure** -Device is cleaned of all persistent storage data. use this to update your device to a newer version of the OS.

1. Download the Update Loader Package 55X0w65HxxUL025700.zip \ 55X0w65HxxUC025700.zip
2. Unzip 55X0w65HxxUL025700.zip \ 55X0w65HxxUC025700.zip package
  - a. Copy all files into either the \Temp folder on the device or at the root directory of a Storage Card.
  - b. If the contents are copied to SD card then place the SD card in the device to be upgraded.
  - c. Place the device to be upgrade on an A/C power.
  - d. Navigate to the SD Card or \Temp folder and invoke the program STARTUPDLDR.EXE.
  - e. The update will take about 5 minutes to complete. Please do not remove the device from A/C power during this time.
  - f. Once the download completes and the system reboots, the update is complete and the device is ready for use.

### Airbeam Users:

**Standard Update Procedure** - This method erases all data in the Persistent storage of the device.

1. Download the Airbeam OSUpdate Package 55X0w65HxxAB025700.apf \ 55X0w65HxxAC025700.apf
2. Apply the Airbeam Update package
3. Once the download completes and the system reboots, the update is complete and the device is ready for use.

### Downgrade to v01.57.04:

#### Standard Downgrade Procedure:

1. Download the Update Loader Package 55X0w65HxxUL015704.zip
2. Unzip the package and copy all files into either the \Temp folder on the device or at the root directory of a Storage Card.
3. If the contents are copied to SD card then place the SD card in the device to be upgraded.
4. Place the device to be upgrade on an A/C power.
5. Navigate to the SD Card or \Temp folder and invoke the program STARTUPDLDR.EXE.

6. The update will take about 5 minutes to complete. Please do not remove the device from A/C power during this time.
7. Once the download completes and the system reboots, the update is complete and the device is ready for use.

## **Part Number and Release Date**

55X0w65HcpUL025700  
55X0w65HcpUC025700  
55X0w65HcpAB025700  
55X0w65HcpAC025700  
55X0w65HctUL025700  
55X0w65HctUC025700  
55X0w65HctAB025700  
55X0w65HctAC025700  
55X0w65HkoUL025700  
55X0w65HkoUC025700  
55X0w65HkoAB025700  
55X0w65HkoAC025700  
55X0w65HsiUL025700  
55X0w65HsiUC025700  
55X0w65HsiAB025700  
55X0w65HsiAC025700  
55X0w65HitUL025700  
55X0w65HitUC025700  
55X0w65HitAB025700  
55X0w65HitAC025700  
55X0w65HfrUL025700  
55X0w65HfrUC025700  
55X0w65HfrAB025700  
55X0w65HfrAC025700  
55X0w65HdeUL025700  
55X0w65HdeUC025700  
55X0w65HdeAB025700  
55X0w65HdeAC025700  
55X0w65HjpUL025700  
55X0w65HjpUC025700  
55X0w65HjpAB025700  
55X0w65HjpAC025700

February 09, 2018