
Release Notes – Zebra TC20 and TC25 Android N LifeGuard Update 01 - SPR36685 for BSP 04-14-30-0-NG-00-M1 (GMS)

Contents

[Description](#)

[Device Compatibility](#)

[Component Contents/Updates](#)

[Installation Requirements](#)

[Installation Instructions](#)

[Downloadable Software included in this Release](#)

Description

This release contains the software package which resolves image distortion issue while scanning a barcode using any application.

This package is compatible with the TC20 and TC25 GMS products.

Note: Devices manufactured after 20MAR19 should be flashed with LifeGuard update 01 - SPR36685 patch or LifeGuard Update -12 (CFE-TC2X-N-XX-041430-G-00-12.zip) or higher LG patches.

Android Security Patch Level: February 5, 2018

Use the below link to see the Android Security bulletin for more information:

<https://source.android.com/security/bulletin/>

1. LifeGuard Patch 01 - SPR36685 Updates:

📁 T2XXJN30APUWW41430_1.zip (GMS)

- Updated below mentioned components:
 - Scanning Framework – 19.8.29.0
 - MXMF – Version 7.2.1.1

- DataWedge – Version 6.7.47
 - SPR36685 - Resolved an issue wherein image distortion issue was observed while scanning a barcode using any application.

Device Compatibility

This software release has been approved for Android TC20 Nougat GMS models mentioned below.

Device	Operating System
TC200J-10C112A6	Android N GMS ROW – EMEA, LATAM, APAC & Canada
TC200J-10C112US	Android N GMS US Only
TC200J-10A111US	Android N GMS US Only
TC200J-10A111A6	Android N GMS ROW – EMEA, LATAM, APAC & Canada
TC200J-10C213A6	Android N GMS ROW – EMEA, LATAM, APAC & Canada (Premium SKU)
TC200J-10C213US	Android N GMS US Only (Premium SKU)
TC200J-10A111TN	Android N GMS TUNISIA Only
TC200J-10C112TN	Android N GMS TUNISIA Only
TC200J-10C213IA	Android N GMS INDIA (Premium SKU)
TC200J-10C112IA	Android N GMS INDIA
TC200J-10A111IA	Android N GMS INDIA
TC200J-1KC111A6	Android N GMS ROW EMEA, LATAM, APAC & Canada (Keyboard SKU)
TC200J-1KC111IA	Android N GMS INDIA (Keyboard SKU)
TC200J-1KC111TN	Android N GMS TUNISIA (Keyboard SKU)
TC200J-1KC111US	Android N GMS US (Keyboard SKU)

This software is also approved for Android TC25 Nougat GMS models mentioned below

Device	Operating System
TC25AJ-10C102A6	Android N GMS ROW – EMEA
TC25AJ-10B101A6	Android N GMS ROW – EMEA
TC25BJ-10C102A6	Android N GMS ROW – EMEA & APAC
TC25BJ-10B101A6	Android N GMS ROW – EMEA & APAC
TC25BJ-10C102IA	Android N GMS ROW - INDIA
TC25BJ-10B101IA	Android N GMS ROW - INDIA
TC25BJ-10C102BR	Android N GMS ROW - BRAZIL
TC25BJ-10B101BR	Android N GMS ROW - BRAZIL
TC25BJ-10C102TN	Android N GMS ROW - TUNISIA
TC25BJ-10B101TN	Android N GMS ROW - TUNISIA
TC25BJ-10C102JP	Android N GMS ROW - JAPAN
TC25BJ-10B101JP	Android N GMS ROW - JAPAN
TC25AJ-10C102US	Android N GMS NORTH AMERICA - US
TC25AJ-10B101US	Android N GMS NORTH AMERICA - US
TC25BJ-10B101ID	Android N GMS ROW - INDONESIA
TC25BJ-10C102ID	Android N GMS ROW - INDONESIA

Component Contents/Updates

Component / Description	Version
Product Build Number	04-14-30-0-NG-00-M1
Device Patch Version	1_SPR36685_1
Android Version	7.1.2
Wi-Fi	FUSIONLITE_QA_1_0.0.0.015_N

Installation Requirements

HW Requirements

- Windows PC running Windows 7/10 32/64 bits
- USB Type C Cable
- Micro SD Card with at least 2GB capacity (optional)

SW Requirements

Please make sure following components are installed on your computer before commencing OS installation.

- Zebra Android USB Driver V2.2 or higher
- Android Debug Bridge version 1.0.39 or higher
- TC20/TC25 GMS Android OS Release Images

Image Compatibility

To use this Update, the terminal must have the BSP 04-14-30-0-NG-00-M1 installed as the baseline OS.

Installation Instructions

Using the “adb sideload” method

Assumptions

1. ADB installed on PC
 2. TC20/TC25 has Developer options enabled
 3. USB debugging ON Procedure
1. Plug the TC20/TC25 into the USB & Charging Cable and then the Cable to the PC. If you have a Cradle with USB connectivity, connect it now.
 2. You may need to pull down notification bar, and tap on the notification which says, “USB charging this device”, and change it to “Transfer files”.
 3. Open Command Prompt on PC, run “adb devices” and check to see if you can see the device’s serial number... If yes, proceed... if not you will need to get the PC set up with the proper drivers or install an External SD Card.
 4. You may also get a pop up on your PC (Win 7) that you will be connected as a Portable Media Player... this can be ignored.
 5. Entering Recovery Mode
 - a. Choice 1: In Command Prompt, type “adb reboot recovery” and click enter.
 - b. Choice 2:
 - i. Reboot and hold PTT key

- ii. When Zebra Technologies logo appears on the screen Release the PTT Key
6. Your TC20/TC25 will reboot and take you to Android Recovery screen.
7. To select Sideload Method
 - a. Use the Volume + and – to highlight, “Apply update from ADB” and press the Power Key to select it
8. With your Command Prompt, open, type “adb sideload” and add a space and then drag and drop the zip file which you want to apply to the device and press enter.
 - a. When the file download starts, the command window will show progress with a percentage completed.
 - b. Device display will show a series of messages indicating it is downloading, verifying and installing the image on to the device.
9. After successful update, the device will auto reboot and you see Zebra on top and POWERED BY android at the bottom and after about 10 second will transition to the TC20/TC25 Touch Computer splash screen with 5 dancing white dots at bottom... it will stay at this screen for up to 4 minutes and then present the “Welcome Screen”.
10. To make sure the OS Patch Update took place, once the initial setup is complete;
 - a. Go to “Settings” and scroll down to “About phone” and look at the “Patch version”. It should state the Patch Version as “1_SPR36685_1”.
11. Now you are all set to use your TC20/TC25.

Using External SD Card

1. Plug the TC20/TC25 into the USB & Charging Cable and then the Cable to the PC. If you have a Cradle with USB connectivity, connect it now.
2. You may need to pull down notification bar, and tap on the notification which says, “USB charging this device”, and then change it to “Transfer files”.
3. You may also get a pop up on your PC (Win 7) that you will be connected as a Portable Media Player... this can be ignored.
4. Copy the required files to the SD Card. This can be done in two ways
 - a. Copy the files to the Micro SD card with the help of a SD Adapter which gets inserted to the SD slot of your PC/Laptop/SD Writer.
 - b. Directly transfer files to the Micro SD card which is inserted in to the back of the device. Please refer to the user guide on how to open the back door and inserting the SD card to the device.
5. Entering Recovery Mode
 - a. Choice 1: In Command Prompt, type “adb reboot recovery” and click enter. b. Choice 2:
 - i. Reboot and hold PTT key
 - ii. When Zebra Technologies logo appears on the screen Release the PTT Key
6. Your TC20/TC25 will reboot and take you to Android Recovery screen.
7. Applying update via External SD card
 - a. Use the Volume + and – to highlight select option to “Apply update from SD card” and press the Power Key to select it
 - b. Use the Volume + and – to highlight package to be installed (downloaded Zip file) and press the Power Key to select it.
8. After successful update, the device will auto reboot and you see Zebra on top and POWERED BY android at the bottom and after about 10 second will transition to the TC20/TC25 Touch Computer splash screen with 5 dancing white dots at bottom... it will stay at this screen for up to 4 minutes and then present the “Welcome Screen”.

9. To make sure the OS Update took place, once the initial setup is complete;
 - a. Go to “Settings” and scroll down to “About phone” and look at the “Patch version”. It should state the Patch Version as “1_SPR36685_1”.
10. Now you are all set to use your TC20/TC25.

Downloadable Software Included in this Release

Filename	Description
T2XXJN30APUWW41430_1.zip	OS Update patch for BSP 04-14-30-0-NG-00-M1.

Last Revised: 03-27-2019