



Release Notes

Scanner Management Solution (SMS) for Linux v1.3 *October 2020*

Contents

Overview	1
Device Compatibility	3
Version History.....	3
Components.....	4
Installation Options (Supported Distributions).....	5

Overview

The Scanner Management Solution (SMS) enables your enterprise to remotely manage its Zebra scanners. In addition to accessing asset tracking information and statistics, the SMS (which runs on the scanner’s host PC) can remotely set parameters and update firmware.

Remote Management Functionality

1. Asset information is available within the log file
 - a. The SMS detects scanners, if they are connected to the host at the time the SMS is launched.
 - b. The scanner will be detected if it is in a supported “Communication Protocol Switching” mode, see section below.
2. Configuration settings can be loaded to a scanner using a SMS Package
3. Firmware can be loaded to a scanner using a SMS Package
4. Both configuration settings and firmware can be loaded using a SMS Package



5. A log file is available with asset information and actions performed.
6. Not supported
 - a. Ability to query statistics

Supported Scanners

1. The SMS for Linux supports the connection of the following scanners to a Linux computer.
 - a. One corded scanner plugged in at a time like the DS8108
 - b. One cordless scanner and cradle like the DS8178 / std cradle
 - c. One MP7000
 - d. One MP7000 and CSS
 - e. One MP7000 and CSS and DS4308
2. Not supported
 - a. One MP7000 and DS8178 with cradle

Supported Communication Protocols

1. Cable Type
 - a. The SMS for Linux requires a USB cable.
2. Data
 - a. For details on the supported data communication protocols (transmission of bar code data), see the “Linux SDK Release Notes” document.
3. Communication Protocol Switching
 - a. The SMS for Linux supports com protocol switching to and from these com modes:
 - b. USB HID Keyboard
 - c. USB SNAPI
 - d. USB IBM Handheld
 - e. Not supported – USB IBM Tabletop
4. Management - The management of the scanner occurs over
 - a. USB SNAPI
 - b. USB IBM Handheld
 - c. Not supported – USB IBM Tabletop

SMS Package Generation

1. The SMS Package for Linux is generated using the SMS wizard within 123Scan.
2. To use the SMS, put a SMS Package into SMS’ download folder. For the download folder location, see the Components section below.

Installation of the SMS

1. The SMS is installed using a Debian or RPM packages depending on your OS distribution.
2. The installation path must use the folder structure listed below
3. The installation software can be configured for a silent installation

Launching the SMS

1. The SMS is a Linux application that is launched using a Linux’s Cron job (a time-based job scheduler in Linux) or the SMS can be launched manually.

Log File Capabilities

1. The SMS logs are contained within the log folder



2. The SMS' customer facing log contains the following:
 - a. Asset tracking information before running and after running the SMS
 - b. If a configuration file was loaded
 - c. If firmware was loaded
 - d. A time date stamp on an event
3. The SMS generates debug logs, available for engineering analysis

For the latest SMS updates, please visit [Zebra SMS for Linux](#)

For support, please visit <http://www.zebra.com/support>.

Device Compatibility

For the compatible devices list, please visit following page.

<https://www.zebra.com/us/en/support-downloads/software/utilities/scanner-management-solution-for-linux.html>

Version History

Version 1.3.1-13 – 10/2020

1. Bug fix – firmware update shows the correct scanner host mode when the scanner in IBMHID.

Version 1.3.1-12 – 04/2020

1. Added asset information (model number, serial number, date of manufacture, firmware version, configuration file name) to SMS log file. A default package is now present in the download folder. The default package causes the logging of asset information at SMS startup, even if the customer has not loaded a SMS Package.
2. A default package is now present in the download folder.

Version 1.3.1-9 – 10/2019

1. Added CentOS 7.3 support.
2. Added Debian 9.5 support.
3. Added C++ 11 support.

Version 1.3.1-7 – 07/2019

1. Added ability to execute the SMS using an external Java program.

Version 1.3.0 – 11/2018

1. Added Retry logic, if firmware update fails, will attempt to reload firmware up to 3 times
2. Support added for following distributions
 - a. CentOS 6.0 32bit



- b. SLES 11 SP2 32bit
- c. SLES 11 SP3 64bit and 32bit
- d. Open SUSE 13.1 64bit and 32bit
- e. Redhat 6.3 32bit
- f. Ubuntu 12.04 32bit and 64bit
- g. Debian 8 64bit and 32bit

Version 1.2.0 – 08/2018

- 3. Firmware/Configuration update through management mode IBMHH.
- 4. Firmware/Configuration update for cascaded and Bluetooth scanners.
 - a. Direct connected cradle paired Bluetooth scanner.
 - b. Direct connected MP6000/MP7000 with auxiliary scanner.
 - c. Multiple directly connected scanner support (up to 5 devices).
- 5. Supported distributions
 - a. SUSE Linux Enterprise Server 12, 64bit architectures.
 - b. Ubuntu 14.04, 64bit architecture.
 - c. Ubuntu 14.04, 32bit architecture.

Version 1.1.0 – 06/2017

- 1. Scanner Management Solution support for Linux CoreScanner driver v4.0.

Version 1.0.0 – 04/2017

- 1. Initial release of the Scanner Management Solution.
- 2. Firmware update for corded scanners through SNAPI.
- 3. Configuration push for corded scanners through SNAPI.
- 4. Parameter barcode scanning enabling/disabling through SNAPI.
- 5. Assets tracking information before/after scanner management.

Components

If the default install location is not changed, the components are installed in the following folders:

Component	Location
SMS Program folder	/usr/share/zebra-scanner/sms
SMS Package download folder	/usr/share/zebra-scanner/sms/download
SMS Default log folder	/usr/share/zebra-scanner/sms/logs
Launch SMS as an Application	/usr/share/zebra-scanner/sms/SMS
Release notes (This file)	/usr/share/doc/zebra-scanner-managementsolution/ Release_Notes.pdf



Installation Options (Supported Distributions)

The Scanner Management Solution can only run as an application. This application can be initiated using a terminal command.

- For the installation of Scanner Management Solution, CoreScanner Driver v4.1 or an above version is required.
- Installation of the software can be done through Software Center or the terminal command.

Package Types

Installation Options	CentOS 7.3	CentOS 6.0	SLES 12 SP2	SLES 11 SP3	SLES 11 SP2	Open Suse 13.1	Red Hat 6.3	Ubuntu 14.04	Ubuntu 12.04	Deban 9.5	Debian 8	
RPM_Package_x86_64bit	X	NA	X	X	NA	X	NA	NA	NA	NA	NA	X86 Architecture
RPM_Package_x86_32bit	NA	X	NA	X	X	X	X	NA	NA	NA	NA	X86 Architecture
Debian_Package_x86_64bit	NA	NA	NA	NA	NA	NA	NA	X	X	X	X	X86 Architecture
Debian_Package_x86_32bit	NA	NA	NA	NA	NA	NA	NA	X	X	X	X	X86 Architecture

Minimum PC Requirements

- Hardware Requirements
 - Pentium Dual-Core E214 1.6GHz or Pentium Mobile Dual-Core T2060 or Pentium Celeron E1200 1.6GHz.
 - 2GB RAM 1.2 GB free hard drive space.
 - USB port, 1.1 or higher, for the connection of USB Scanners.

NOTE: SMS v1.3 must use SMS packages created with 123Scan2 v 4.1 or higher.