

Release Notes - MC67NA JB - BSP v012814 (REVA)/v030515 (REVB) - Stagefright Security Vulnerability in Android Devices - SPR 28147

[Introduction](#)
[Description](#)
[Contents](#)
[Device Compatibility](#)
[Installation Requirements](#)
[Installation Instructions](#)
[Part Number and Release Date](#)

Introduction

SPR28147 - Security vulnerabilities have been identified in the Android Stagefright multimedia libraries.

Patch to fix SPR28147 is being provided for MC67NA JB Devices.

Description

Vulnerabilities were discovered in the Android Stagefright multimedia libraries.
The patch addresses the following:

CVE-2015-1538
CVE-2015-1539
CVE-2015-3824
CVE-2015-3826
CVE-2015-3827
CVE-2015-3828
CVE-2015-3829
CVE-2015-3864

Contents

SPR28147_MC67NA_JB_en_030515_v1_2.zip (MC67NA JB Stagefright recovery update patch- applicable for both REVA and REVB builds)

SPR28147_MC67JBxxen030515v1_2.apf (MC67NA JB Stagefright patch AirBEAM package - applicable for both REVA and REVB builds)

Device Compatibility

This software release has been approved for use with the following Zebra devices,

Device	Operating System	OEM Version
MC67NA	Android JB 4.1.1	v012814 (REVA) v030515 (REVB)

Installation Requirements

This SW is intended for the MC67NA JB device running 01-4AJ11-J-0800-0005-00-M1-012814 (REVA) /01-4AJ11-J-2200-0001-00-M1-030515 (REVB) builds only.

Installation Instructions

For NORMAL installation of the PATCH:

1. Connect the USB cable from your PC to the device and enable USB mass storage mode on the device.
2. On your PC you should see an internal and external USB mass storage drive (SD card) appears in the File Explorer and copy the "SPR28147_MC67NA_JB_en_030515_v1_2.zip" file to any storage.
3. Press and hold on the device the Power button, Scan/Action button and Vol+ button until the screen is turned OFF.
4. Release the Power and Scan/Action buttons and continue to hold Vol+ button.
5. The device should enter to Recovery update mode.
6. Release Vol+.
7. Click on Vol+ or Vol- to navigate and select appropriated storage.
8. Click on Scan/Action button to select the option.
9. Click on Vol+ or Vol- to navigate to the SPR28147_MC67NA_JB_en_030515_v1_2.zip file.
10. Click Scan/Action button to select the recovery update zip file.
11. Click on Vol+ or Vol- to navigate reboot system now and Click on Scan/Action button to reboot the device.
12. To verify that the patch is installed, you can check for the existence of the "SPR28147_MC67NA_JB_en_030515_v1_2.txt" in /system/patch/. This '.txt' file will contain the SPR#s that are part of the patch and the patch build date.
SPR28147_MC67NA_JB_en_030515_v1_2.txt file contents:
08-18-2015
SPR28147

For MSP (REMOTE) installation of the PATCH:

Please refer Mobility Service Platform deployment guide for instructions.

Part Number and Release Date

N/A

August, 2015